



	Discrete-time systems with time-varying time delay: Stability and stabilizability
Auteurs: Authors:	El-Kébir Boukas
Date:	2006
Type:	Article de revue / Article
Référence: Citation:	Boukas, EK. (2006). Discrete-time systems with time-varying time delay: Stability and stabilizability. Mathematical Problems in Engineering, 2006, 42489. https://doi.org/10.1155/mpe/2006/42489

Document en libre accès dans PolyPublie Open Access document in PolyPublie

URL de PolyPublie: PolyPublie URL:	https://publications.polymtl.ca/3385/
Version:	Version officielle de l'éditeur / Published version Révisé par les pairs / Refereed
Conditions d'utilisation: Terms of Use:	CC BY

Document publié chez l'éditeur officiel Document issued by the official publisher

Titre de la revue: Journal Title:	Mathematical Problems in Engineering (vol. 2006)
Maison d'édition: Publisher:	Hindawi
URL officiel: Official URL:	https://doi.org/10.1155/mpe/2006/42489
Mention légale: Legal notice:	

DISCRETE-TIME SYSTEMS WITH TIME-VARYING TIME DELAY: STABILITY AND STABILIZABILITY

EL-KÉBIR BOUKAS

Received 7 December 2005; Accepted 2 January 2006

This paper deals with the class of linear discrete-time systems with varying time delay. The problems of stability and stabilizability for this class of systems are considered. Given an upper bound and a lower bound on the time-varying delay, sufficient conditions for checking the stability of this class of systems are developed. A control design algorithm is also provided. All the results developed in this paper are in the LMI formalism which makes their solvability easier using existing tools. A numerical example is provided to show the effectiveness of the established results.

Copyright © 2006 El-Kébir Boukas. This is an open access article distributed under the Creative Commons Attribution License, which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

1. Introduction

It is well established in the literature that time delay is the cause of performance degradations for dynamical systems. It can even be, in some circumstances, the cause of instability of the system that we would like to control if such time delay is not taken into account during the design phase. Time delay may occur either in continuous-time or discrete-time systems and may be constant or time varying.

The control of systems with time delay has been a hot subject of research in the last decades. Stability and stabilizability problems either for the continuous-time and discrete-time deterministic and stochastic systems with time delay have been tackled and interesting results have been reported in the literature. The reported results are divided into delay-independent and delay-dependent conditions. The delay-independent conditions present more conservatism than delay-dependent conditions since they do not depend on the delay in the system.

For deterministic class of linear systems with time delay, we have seen an increasing interest during the last two decades. Many papers, mainly on the class of deterministic continuous-time linear systems with time delay have been published. Stability and stabilizability problems have been studied and interesting results are available in the literature.

However, for deterministic class of discrete-time linear systems with constant time delay only few results have been reported in the literature. The main reason for this, we believe, is that this kind of systems can be transformed to an equivalent system without time delay and then we can use the known results on stability and stabilizability. For more information on some of the developed results for this class of systems, we refer the reader to Boukas and Liu [1], Kim and Park [6], Song and Kim [9], Mukaidani et al. [7], Chang et al. [4], Gao et al. [5], and references therein.

The problems of stochastic stability and stochastic stabilizability have also been tackled by many authors and recently we have seen the publication of different results ranging from delay independent to delay dependent for the continuous-time and the discrete-time cases. Several situations were considered including constant time delay, time-varying delay and mode-dependent time delay for the continuous-time systems and constant and mode-dependent time delay for discrete-time systems. For more details on this subject we refer the reader to Boukas and Liu [2], Boukas and Liu [1], and the references therein, respectively, for the continuous-time and discrete-time cases. Other results can be found in [8], [3], and the references therein.

To the best of the author knowledge, the mode-dependent time-delay case for the class of discrete-time linear systems with varying time delay has not been fully investigated and this will be the subject of this paper. Among the references that tackled the delay-dependent stability and the stabilizability problems for linear systems with varying time delay, we quote those of Mukaidani et al. [7], Chang et al. [4], Gao et al. [5], and the references therein. The goal of this paper is to develop new LMI-based delay-dependent sufficient conditions for stability and stabilizability for linear discrete-time systems with varying time delay in the state.

The paper is organized as follows. In Section 2, the problem is stated and the objectives of the paper are formulated. The problem of stability for the discrete-time linear system with varying time delay is examined and delay-dependent sufficient conditions are developed in Section 3. In Section 4, the stabilizability problem is investigated and delay-dependent conditions are established. In addition, a design algorithm that stabilizes the resulting closed-loop system is provided. A numerical example is given to show the usefulness of the proposed theoretical results in Section 5.

2. Problem statement

The dynamics of the system we consider in this paper are assumed to be described by the following difference equation:

$$x_{k+1} = Ax_k + A_d x_{k-d_k} + Bu_k \quad x_k = \phi_k, \ k \in [-\overline{d}, ..., 0],$$
 (2.1)

where $x_k \in \mathbb{R}^n$ is the state at instant k, $u_k \in \mathbb{R}^p$ is the control input at instant k, the matrices $A \in \mathbb{R}^{n \times n}$, $A_d \in \mathbb{R}^{n \times n}$, and $B \in \mathbb{R}^{n \times p}$ are constant matrices and d_k is a positive integer representing the time delay of the system that we assume to be time dependent and satisfies the following:

$$0 \le d \le d_k \le \overline{d},\tag{2.2}$$

where \underline{d} and \overline{d} are known to be positive and finite integers.

The aim of this paper is to establish the sufficient conditions that guarantee the stability of the class of system (2.1). We will also tackle the stabilizability problem of this class of systems. LMI-based delay-dependent conditions either for stability or stabilization are targeted.

The control law we will use in the paper is given by the following:

$$u_k = Kx_k, (2.3)$$

where *K* is the control gain to be computed.

Notation 2.1. The notation used in this paper is quite standard. \mathbb{R}^n and $\mathbb{R}^{n\times m}$ denote, respectively, the set of the *n* dimensional space of real vectors and the set of all $n \times m$ real matrices. The superscript " \top " denotes the transpose and the notation $X \ge Y(\text{resp.}, X > 1)$ Y) where X and Y are symmetric matrices, meaning that X - Y is positive semidefinite (resp., positive definite). P > 0 means that P is symmetric and positive definite. I is the identity matrix with compatible dimension. We define $\mathbf{x}_l(k) = x_{k+l}, k - d_k \le l \le k$, noted in the sequel by \mathbf{x}_k .

3. Stability

In this section, we present delay-dependent conditions that can be used to check if the system we are considering is stable. The following result gives what conditions to be satis field to guarantee that the system (2.1) for $u_k = \text{for } k \ge 0$ is stable.

Theorem 3.1. For a given set of upper and lower bounds \overline{d} and d for the time varying delay r_k , if there exist symmetric and positive-definite matrices $P_1 > 0$, Q > 0 and R > 0, and matrices P_2 and P_3 such that the following LMIs hold:

$$Q < R, \tag{3.1}$$

$$\begin{bmatrix} Q + (\overline{d} - \underline{d})R - P_1 - A^{\mathsf{T}}P_2 - P_2^{\mathsf{T}}A & -A^{\mathsf{T}}P_3 + P_2^{\mathsf{T}} & -P_2^{\mathsf{T}}A_d \\ -P_3^{\mathsf{T}}A + P_2 & P_1 + P_3 + P_3^{\mathsf{T}} & -P_3^{\mathsf{T}}A_d \\ -A_d^{\mathsf{T}}P_2 & -A_d^{\mathsf{T}}P_3 & -Q \end{bmatrix} < 0, \tag{3.2}$$

then, system (2.1) is stable.

Proof. To prove our theorem, let us consider the following change of variables:

$$x_{k+1} = y_k \quad 0 = -y_k + Ax_k + A_d x_{k-d_k}. \tag{3.3}$$

Define $\widetilde{x}_k^{\top} = [x_k \ y_k \ x_{k-d_k}]^{\top}$, and consider the following Lyapunov-Krasovskii candidate functional:

$$V(\widetilde{\mathbf{x}}_k) = V_1(\widetilde{\mathbf{x}}_k) + V_2(\widetilde{\mathbf{x}}_k) + V_3(\widetilde{\mathbf{x}}_k)$$
(3.4)

4 Discrete-time systems with time-varying time delay

with

$$V_1(\widetilde{\mathbf{x}}_k) = \widetilde{\mathbf{x}}_k^{\top} E^{\top} P \widetilde{\mathbf{x}}_k, \qquad V_2(\widetilde{\mathbf{x}}_k) = \sum_{l=k-d_k}^{k-1} x_l^{\top} Q x_l, \qquad V_3(\widetilde{\mathbf{x}}_k) = \sum_{l=-\bar{d}+2}^{-\underline{d}+1} \sum_{m=k+l-1}^{k-1} x_m^{\top} R x_m,$$

$$(3.5)$$

where Q > 0 and R > 0, and E and P are, respectively, singular and nonsingular matrices with the following forms:

$$E = \begin{bmatrix} \mathbb{I} & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}, \qquad P = \begin{bmatrix} P_1 & 0 & 0 \\ P_2 & P_3 & 0 \\ 0 & 0 & \mathbb{I} \end{bmatrix}$$
(3.6)

with P_1 is a symmetric and positive-definite matrix.

The difference $\Delta V(\widetilde{\mathbf{x}}_k)$ is given by

$$\Delta V(\widetilde{\mathbf{x}}_k) = \Delta V_1(\widetilde{\mathbf{x}}_k) + \Delta V_2(\widetilde{\mathbf{x}}_k) + \Delta V_3(\widetilde{\mathbf{x}}_k). \tag{3.7}$$

Let us now compute $\Delta V_1(\mathbf{x}_k)$:

$$\Delta V_1(\widetilde{\mathbf{x}}_k) = V_1(\widetilde{\mathbf{x}}_{k+1}) - V_1(\widetilde{\mathbf{x}}_k) = \widetilde{\mathbf{x}}_{k+1}^{\top} E^{\top} P \widetilde{\mathbf{x}}_{k+1} - \widetilde{\mathbf{x}}_k^{\top} E^{\top} P \widetilde{\mathbf{x}}_k$$

$$= y_k^{\top} P_1 y_k - x_k^{\top} P_1 x_k = y_k^{\top} P_1 y_k - 2 \begin{bmatrix} x_k^{\top} & 0 & 0 \end{bmatrix} P_1 \begin{bmatrix} \frac{1}{2} x_k \\ 0 \\ 0 \end{bmatrix}$$
(3.8)

which can be rewritten using the fact that $0 = -y_k + Ax_k + A_dx_{k-d_k}$ as follows:

$$\Delta V_{1}(\widetilde{\mathbf{x}}_{k}) = \widetilde{\mathbf{x}}_{k}^{\top} \begin{bmatrix} 0 & 0 & 0 \\ 0 & P_{1} & 0 \\ 0 & 0 & 0 \end{bmatrix} - P^{\top} \begin{bmatrix} \frac{1}{2} \mathbb{I} & 0 & 0 \\ A & -\mathbb{I} & A_{d} \\ 0 & 0 & 0 \end{bmatrix} - \begin{bmatrix} \frac{1}{2} \mathbb{I} & A^{\top} & 0 \\ 0 & -\mathbb{I} & 0 \\ 0 & A_{d}^{\top} & 0 \end{bmatrix} P \widetilde{\mathbf{x}}_{k}.$$
 (3.9)

For $V_2(\widetilde{\mathbf{x}}_k)$, by standard manipulation, we have

$$\Delta V_2(\widetilde{\mathbf{x}}_k) = V_2(\widetilde{\mathbf{x}}_{k+1}) - V_2(\widetilde{\mathbf{x}}_k) = \sum_{l=k+1-d_{k+1}}^k x_l^{\top} Q x_l - \sum_{l=k-d_k}^{k-1} x_l^{\top} Q x_l.$$
 (3.10)

Notice that

$$\sum_{l=k+1-d_{k+1}}^{k} x_{l}^{\top} Q x_{l} = \sum_{l=k+1-d_{k+1}}^{k-\underline{d}} x_{l}^{\top} Q x_{l} + \sum_{l=k+1-\underline{d}}^{k-1} x_{l}^{\top} Q x_{l} + x_{k}^{\top} Q x_{k},$$

$$\sum_{l=k-d_{k}}^{k-1} x_{l}^{\top} Q x_{l} = \sum_{l=k+1-d_{k}}^{k-1} x_{l}^{\top} Q x_{l} + x_{k-d_{k}}^{\top} Q x_{k-d_{k}}.$$
(3.11)

Using this, we can rewrite $\Delta V_2(\mathbf{x}_k)$ as follows:

$$\Delta V_{2}(\widetilde{\mathbf{x}}_{k}) = x_{k}^{\top} Q x_{k} - x_{k-d_{k}}^{\top} Q x_{k-d_{k}} + \sum_{l=k+1-d_{k+1}}^{k-\underline{d}} x_{l}^{\top} Q x_{l} + \sum_{l=k+1-\underline{d}}^{k-1} x_{l}^{\top} Q x_{l} - \sum_{l=k+1-d_{k}}^{k-1} x_{l}^{\top} Q x_{l}.$$
(3.12)

For $V_3(\widetilde{\mathbf{x}}_k)$, one has

$$\Delta V_{3}(\widetilde{\mathbf{x}}_{k}) = \sum_{l=-\bar{d}+2}^{-\bar{d}+1} \sum_{m=k+l}^{k} x_{m}^{\top} R x_{m} - \sum_{l=-\bar{d}+2}^{-\bar{d}+1} \sum_{m=k+l-1}^{k-1} x_{m}^{\top} R x_{m}
= \sum_{l=-\bar{d}+2}^{-\bar{d}+1} \left[\sum_{m=k+l}^{k-1} x_{m}^{\top} R x_{m} + x_{k}^{\top} R x_{k} - \sum_{m=k+l}^{k-1} x_{m}^{\top} R x_{m} - x_{k+l-1}^{\top} R x_{k+l-1} \right]
= \sum_{l=-\bar{d}+2}^{-\bar{d}+1} \left[x_{k}^{\top} R x_{k} - x_{k+l-1}^{\top} R x_{k+l-1} \right] = (\bar{d} - \underline{d}) x_{k}^{\top} R x_{k} - \sum_{l=-\bar{d}+2}^{-\bar{d}+1} x_{k+l-1}^{\top} R x_{k+l-1}
= (\bar{d} - \underline{d}) x_{k}^{\top} R x_{k} - \sum_{l=k+1-\bar{d}}^{k-\bar{d}} x_{l}^{\top} R x_{l}.$$
(3.13)

Notice that $d_k \ge \underline{d}$ for all k, we get

$$\sum_{l=k+1-\underline{d}}^{k-1} x_{l}^{\top} Q x_{l} \leq \sum_{l=k+1-d_{k}}^{k-1} x_{l}^{\top} Q x_{l}, \qquad \sum_{l=k+1-d_{k+1}}^{k-\underline{d}} x_{l}^{\top} Q x_{l} \leq \sum_{l=k+1-\overline{d}}^{k-\underline{d}} x_{l}^{\top} Q x_{l},$$

$$\sum_{l=k+1-\overline{d}}^{k-\underline{d}} x_{l}^{\top} Q x_{l} < \sum_{l=k+1-\overline{d}}^{k-\underline{d}} x_{l}^{\top} R x_{l}, \quad \text{since } Q < R.$$
(3.14)

Finally, by using (3.9), (3.12), and (3.13) together with these inequalities and the condition (3.2), we obtain

$$\Delta V(\widetilde{\mathbf{x}}_k) \le \begin{bmatrix} x_k^\top & y_k^\top & x_{k-d_k}^\top \end{bmatrix} M \begin{bmatrix} x_k \\ y_k \\ x_{k-d_k} \end{bmatrix} < 0, \tag{3.15}$$

where

$$M = \begin{bmatrix} Q + (\overline{d} - \underline{d})R - P_1 - A^{\top}P_2 - P_2^{\top}A & -A^{\top}P_3 + P_2^{\top} & -P_2^{\top}A_d \\ -P_3^{\top}A + P_2 & P_1 + P_3 + P_3^{\top} & -P_3^{\top}A_d \\ -A_d^{\top}P_2 & -A_d^{\top}P_3 & -Q \end{bmatrix}.$$
(3.16)

This implies that the system is stable.

Remark 3.2. The conditions of this theorem are delay dependent and can solve many stability problems for discrete-time systems with time-varying delay. These conditions are more appropriate for practical systems since practically it is impossible to know exactly the delay but lower and upper bounds are always possible.

6 Discrete-time systems with time-varying time delay

Remark 3.3. In practice we are always interested in knowing what would be the maximum time delay such that the system can remain stable. The answer to this question can be obtained by solving the following nonlinear optimization problem:

$$\max_{\bar{d}>0, P_1>0, P_2, P_3, Q>0, R>0} \bar{d} \quad \text{s.t (3.1)} - (3.2). \tag{3.17}$$

When time delay is constant, that is, $d_k = d$ and $d = \bar{d} = \underline{d}$, the results given by Theorem 3.1 are replaced by the following ones.

COROLLARY 3.4. If there exist symmetric and positive-definite matrices $P_1 > 0$, Q > 0, and matrices P_2 and P_3 such that the following LMI holds:

$$\begin{bmatrix} Q - P_1 - A^{\mathsf{T}} P_2 - P_2^{\mathsf{T}} A & -A^{\mathsf{T}} P_3 + P_2^{\mathsf{T}} & -P_2^{\mathsf{T}} A_d \\ -P_3^{\mathsf{T}} A + P_2 & P_1 + P_3 + P_3^{\mathsf{T}} & -P_3^{\mathsf{T}} A_d \\ -A_d^{\mathsf{T}} P_2 & -A_d^{\mathsf{T}} P_3 & -Q \end{bmatrix} < 0, \tag{3.18}$$

then system (2.1) is stable.

Remark 3.5. The conditions of this corollary are delay independent, which makes them conservative.

4. Stabilizability

The aim of this section is to design a state-feedback controller which stabilizes the resulting closed-loop system. Using the controller expression (2.3) and system dynamics (2.1), we get the following dynamics for the closed-loop system:

$$x_{k+1} = [A + BK]x_k + A_d x_{k-d_k}. (4.1)$$

If we let $\overline{A} = A + BK$, based on the results on stability, the closed-loop system will be stable if there exist symmetric and positive-definite matrices $P_1 > 0$, Q > 0, R > 0, and matrices P_2 and P_3 that satisfy the following LMIs:

$$Q < R,$$

$$\begin{bmatrix} Q + (\overline{d} - \underline{d})R - P_1 - \overline{A}^{\mathsf{T}} P_2 - P_2^{\mathsf{T}} \overline{A} & -\overline{A}^{\mathsf{T}} P_3 + P_2^{\mathsf{T}} & -P_2^{\mathsf{T}} A_d \\ -P_3^{\mathsf{T}} \overline{A} + P_2 & P_1 + P_3 + P_3^{\mathsf{T}} & -P_3^{\mathsf{T}} A_d \\ -A_d^{\mathsf{T}} P_2 & -A_d^{\mathsf{T}} P_3 & -Q \end{bmatrix} < 0.$$

$$(4.2)$$

If we denote by X the inverse of P, we have

$$X = \begin{bmatrix} X_1 & 0 & 0 \\ X_2 & X_3 & 0 \\ 0 & 0 & 1 \end{bmatrix}, \qquad X_1 = P_1^{-1}, \qquad 0 = P_2 X_1 + P_3 X_2, \qquad X_3 = P_3^{-1}.$$
 (4.3)

Pre- and postmultiplying the second LMI, respectively, by X^{\top} and X and using these relations, we get

$$\begin{bmatrix} X_{1}^{\top}QX_{1} + (\overline{d} - \underline{d})X_{1}^{\top}RX_{1} - X_{1} + X_{2}^{\top}P_{1}X_{2} & \star & \star \\ -AX_{1} - BKX_{1} + X_{2} + X_{3}^{\top}P_{1}X_{2} & X_{3}^{\top}P_{1}X_{3} + X_{3} + X_{3}^{\top} & \star \\ 0 & -A_{d}^{\top} & -Q \end{bmatrix} < 0, \quad (4.4)$$

which can be rewritten as after letting $Y = KX_1$:

$$\begin{bmatrix} X_{1}^{\top}QX_{1} + (\overline{d} - \underline{d})X_{1}^{\top}RX_{1} - X_{1} & \star \\ -AX_{1} - BY + X_{2} & X_{3} + X_{3}^{\top} \end{bmatrix} + \begin{bmatrix} X_{2}^{\top} \\ X_{3}^{\top} \end{bmatrix} P_{1} \begin{bmatrix} X_{2} & X_{3} \end{bmatrix}$$

$$+ \begin{bmatrix} 0 \\ -A_{d}Q^{-1} \end{bmatrix} Q \begin{bmatrix} 0 & -Q^{-1}A_{d}^{\top} \end{bmatrix} < 0,$$

$$(4.5)$$

which gives in turn

$$\begin{bmatrix}
-X_{1} & \star & \star & \star & \star & \star & \star \\
-AX_{1} - BY + X_{2} & X_{3} + X_{3}^{\top} & \star & \star & \star & \star \\
X_{2} & X_{3} & -X_{1} & \star & \star & \star \\
0 & -Q^{-1}A_{d}^{\top} & 0 & -Q^{-1} & \star & \star \\
X_{1} & 0 & 0 & 0 & -Q^{-1} & \star \\
X_{1} & 0 & 0 & 0 & 0 & -\frac{1}{\overline{d}-d}R^{-1}
\end{bmatrix} < 0. \quad (4.6)$$

Letting $S = Q^{-1}$ and $T = R^{-1}$, we get the following results.

THEOREM 4.1. For a given set of upper and lower bounds on the time-varying delay d_k , \overline{d} , and d, if there exist symmetric and positive-definite matrices $X_1 > 0$, S > 0, and T > 0 and matrices $X_2 > 0$ and $X_3 > 0$ such that the following LMIs hold:

$$\begin{bmatrix}
-X_{1} & \star & \star & \star & \star & \star \\
-AX_{1} - BY + X_{2} & X_{3} + X_{3}^{\top} & \star & \star & \star & \star \\
X_{2} & X_{3} & -X_{1} & \star & \star & \star \\
0 & -SA_{d}^{\top} & 0 & -S & \star & \star \\
X_{1} & 0 & 0 & 0 & -S & \star \\
X_{1} & 0 & 0 & 0 & 0 & -\frac{1}{\overline{d} - \underline{d}}T
\end{bmatrix} < 0,$$
(4.7)

then system (2.1) is stable under the controller (2.3) and the control gain is given by K= YX_{1}^{-1} .

Similarly, when the time delay is constant, that is, $d_k = d$, $d = \bar{d} = \underline{d}$, Theorem 4.1 is reduced to the following corollary.

COROLLARY 4.2. If there exist symmetric and positive-definite matrices $X_1 > 0$ and S > 0 and matrices $X_2 > 0$ and $X_3 > 0$ such that the following LMI holds:

$$\begin{bmatrix}
-X_{1} & \star & \star & \star & \star \\
-AX_{1} - BY + X_{2} & X_{3} + X_{3}^{\top} & \star & \star & \star \\
X_{2} & X_{3} & -X_{1} & \star & \star \\
0 & -SA_{d}^{\top} & 0 & -S & \star \\
X_{1} & 0 & 0 & 0 & -S
\end{bmatrix} < 0, \tag{4.8}$$

then system (2.1) is stable under the controller (2.3) and the control gain is given by $K = YX_1^{-1}$.

Remark 4.3. To find the maximal upper bound of the time delay, \bar{d} , for which system (2.1) is stable, we need to solve the following optimization problem:

$$\max_{\bar{d}>0, X_1>0, X_2, X_3, Y, S>0, T>0} \bar{d} \quad \text{s.t (4.7)}.$$

5. Numerical examples

To illustrate the usefulness of the previous theoretical results, let us give the following numerical example.

Example 5.1. Let us consider a system described by (2.1) and suppose that the system data are as follows:

$$A = \begin{bmatrix} 0 & 1 \\ -2 & -3 \end{bmatrix}, \qquad A_d = \begin{bmatrix} 0.01 & 0.1 \\ 0.0 & 0.1 \end{bmatrix}, \qquad B = \begin{bmatrix} 0.0 \\ 1.0 \end{bmatrix}, \qquad \overline{d} = 10, \qquad \underline{d} = 1.$$

$$(5.1)$$

Solving LMI (4.7), we get

$$X_{1} = \begin{bmatrix} 1.0917 & 0.0116 \\ 0.0116 & 0.4353 \end{bmatrix} > 0, X_{2} = \begin{bmatrix} 0.0017 & 0.0673 \\ -0.0000 & -0.0028 \end{bmatrix},$$

$$X_{3} = \begin{bmatrix} -0.9270 & -0.0263 \\ -0.0184 & -0.4209 \end{bmatrix}, S = \begin{bmatrix} 15.3477 & 0.0758 \\ 0.0758 & 11.3502 \end{bmatrix} > 0, (5.2)$$

$$T = \begin{bmatrix} 12.7561 & 0.0936 \\ 0.0936 & 8.5862 \end{bmatrix} > 0, Y = \begin{bmatrix} 2.2177 & 1.2879 \end{bmatrix}.$$

Therefore, the controller (2.3) with gain

$$K = \begin{bmatrix} 2.0005 & 2.9051 \end{bmatrix} \tag{5.3}$$

stabilizes the system under study.

We have simulated these discrete-time systems with time varying delay with the controller we designed and the results are illustrated in Figure 5.1 and Figure 5.2. These figures show that the closed-loop system is stable under the computed state feedback controller.




Figure 5.1. The behaviors of the states $x_1(t)$ and $x_2(t)$ in function of time t.




Figure 5.2. The behaviors of the control law u(t) in function of time t.

6. Conclusion

In this paper, we have studied the problems of stability and stabilizability for a class of linear discrete-time systems with varying time delay in the state. Sufficient conditions in the LMI formalism have been developed to solve the above problems. An algorithm to design the stabilizing state feedback controller is also provided. A Numerical example is included to demonstrate the effectiveness of the proposed techniques.


References

- [1] E.-K. Boukas and Z. K. Liu, Robust H_{∞} control of discrete-time Markovian jump linear systems with mode-dependent time-delays, IEEE Transactions on Automatic Control **46** (2001), no. 12, 1918–1924.
- [2] ______, Deterministic and Stochastic Time Delay Systems, Birkhäuser, Massachusetts, 2002.
- [3] E.-K. Boukas and P. Shi, \mathcal{H}_{∞} -control for discrete-time linear systems with Markovian jumping parameters, Proceedings of 36th IEEE Conference on Decision and Control, California, 1997, pp. 4134–4139.
- [4] Y.-C. Chang, S.-F. Su, and S.-S. Chen, *LMI approach to static output feedback simultaneous stabilization of discrete-time interval systems with time delay*, Proceedings of International Conference on Machine Learning and Cybernetics, vol. 7, Shanghai, 2004, pp. 4144–4149.
- [5] H. Gao, J. Lam, C. Wang, and Y. Wang, Delay-dependent output-feedback stabilisation of discretetime systems with time-varying state delay, IEE Proceedings-Control Theory and Applications 151 (2004), no. 6, 691–698.
- [6] J. H. Kim and H. B. Park, H[∞] state feedback control for generalized continuous/discrete time-delay system, Automatica 35 (1999), no. 8, 1443–1451.
- [7] H. Mukaidani, S. Sakaguchi, and T. Tsuji, LMI-based neurocontroller for guaranteed cost control of uncertain time-delay systems, Proceedings of IEEE International Symposium on Circuits and Systems, vol. 4, Kobe, 2005, pp. 3047–3050.
- [8] P. Shi, E.-K. Boukas, and R. K. Agarwal, Control of Markovian jump discrete-time systems with norm bounded uncertainty and unknown delay, IEEE Transactions on Automatic Control 44 (1999), no. 11, 2139–2144.
- [9] S.-H. Song and J.-K. Kim, H_{∞} control of discrete-time linear systems with norm-bounded uncertainties and time delay in state, Automatica **34** (1998), no. 1, 137–139.


El-Kébir Boukas: Département de Génie Mécanique, École Polytechnique de Montréal, C.P. 6079, succ. Centre-Ville, Montréal, QC, Canada H3C 3A7 *E-mail address*: el-kebir.boukas@polymtl.ca




















Submit your manuscripts at http://www.hindawi.com











Journal of Discrete Mathematics

